

# NM-SF 50 Adapter

## Electrical Specifications

<b>Frequency Range</b>	DC - 18 GHz
<b>Impedance</b>	50 $\Omega$
<b>Insertion Loss</b>	0.1 dB
<b>VSWR</b>	
DC - 8 GHz	1.15 max
DC - 12.4 GHz	1.20 max
DC - 18 GHz	1.30 max

## Mechanical Specifications

<b>Connector</b>	50 $\Omega$ , N-type male and SMA female
<b>Net weight (approx)</b>	33.6 g

